



**LS-206—  
Ceiling Flush Mount Sensor Light Switch**

**Product Description:**

LS 206 is used to designed for automatically turn ON a light when any human motion is detected and to turn it OFF after you have left the area. The Sensor senses motion in a 360-degree area up to 30 ft. away for Sensor. It is used to connect any lighting source like CFL, Led, tube light, etc. Light Sensor reduces lighting costs by automatically turning On / OFF room, office, or closet lights, when a person enters in. These Sensor saves electrical energy & power. Basic principle of the sensor is to detects "Motion" i.e. to detect "Infrared Energy" of human body and as per this it operates output devices.



**Product Features & Specifications:**

- Ceiling Flush Mount Facility
- Dual Element Sensors
- Switches ON lights on sensing motion
- Keeps lights ON till the motion is detected
- Resettable Fuse is Used for Over Voltage Protection
- Stylish Look

**Technical Specifications**

<b>Power Supply</b>	230VAC/50Hz	<b>Time Setting</b>	3Sec to 40min.
<b>Rated Load</b>	2000W(GLS Lamp) 1000W(CFL/TTL Lamp)	<b>Lux Setting</b>	<05Lux to 1000Lux
<b>Detection Angle</b>	360°C	<b>Detection Range</b>	3M to 7Meter
<b>Humidity</b>	0% to 95% Rh	<b>Installation Height</b>	2.5M to 3Meter

**Applications**



**Realty Automation & Security Systems Pvt. Ltd.**

5,New Sadashiv Peth, Next to Alka Talkies,Pune-411 030. Phone: +91 90110 33259/60.

E-mail: sales@vighnaharta.in

Web: www.vighnaharta.in