



**Realty Automation & Security Systems Pvt. Ltd.**

## **V-Cop ATM AVV Wired Intrusion Alarm Panel**



### **Product Description:**

V-Cop ATM AVV (Audio+Video Verification) is designed considering Safety, Security & Surveillance needs of ATMs. Bank ATMs are subject to theft, vandalism of assets. Though banks are providing for the Security guards, it is expensive to maintain them at every site. Also one has to ensure their presence at all the times which is difficult to manage. Security guards can not provide all the evidence required for identifying the culprits and deterring them from crime.

Assets in ATMs like ATM Machines, Air conditioners, UPS, UPS Batteries are subject to theft. ATM room and backroom doors need monitoring. Other sensors like vibration sensors, glass break sensors, motion sensors can detect corresponding events which could be analysed to detect the intrusion. Our alarm panels identify the abnormal conditions and raise an alert to the central monitoring station (CMS) with the help of wireless (GSM or CDMA) network. They use latest SIA IP DC09 protocol to communicate with monitoring software.

**V-Cop ATM AVV has integrated audio & video recording facility. Two way voice is used to warn the intruders. It is support Up to 4 CCTV Cameras, 1 Audio Microphone and 1 Speaker could be connected along with 34 Sensors inputs to this panel.**

***Panel has Ethernet connectivity or optional GSM/GPRS communication facility.***

V-Cop ATM AVV has provision for installing SMF battery for providing typical backup time of about 7-8 hours. Other features include connection to time attendance switches and reporting to the CMS With zone expansion sensors for 5 ATMs could be connected.

**Realty Automation & Security Systems Pvt. Ltd.**

5, New Sadashiv Peth, Next to Alka Talkies, Pune-411 030. Phone: +91 90110 33259/60.

E-mail: sales@vighnaharta.in

Web: www.vighnaharta.in

## V-Cop ATM AVV Wired Intrusion Alarm Panel

### Technical Specifications:

<b>Power Supply</b>	170-230VAC,50/60Hz	<b>Output</b>	IP base Alert reporting Siren Output (Two Siren) 1 Speaker Output 16*2 LCD Display PFC Relay Output Audio Buzzer
<b>Battery Backup</b>	Up to 7Hr	<b>Optional O/P</b>	RS-485, RS-232, GSM auto Dialer
<b>Input</b>	31 Wired Zones 2 Power Sensing Zones 1 Fire Zone (Conventional) 4 Video Camera Inputs 1 Audio Input	<b>Humidity</b>	0 to 95% Rh
<b>Size</b>	(325x650x120)mm (LxHxW)	<b>Working Temperature</b>	0°C to 50°C

### Application:



**\*Note:- Specification subject to change without notice.**

**Realty Automation & Security Systems Pvt. Ltd.**

5,New Sadashiv Peth, Next to Alka Talkies,Pune-411 030. Phone: +91 90110 33259/60.

E-mail: sales@vighnaharta.in

Web: www.vighnaharta.in